



IMPORTANT SAFETY PRECAUTIONS

Before you begin, read these instructions completely and carefully.

- Be certain electrical power is OFF before and during installation, maintenance and removal.
- Luminaire wiring must be properly grounded in accordance with the NEC and any applicable local code requirements.
- Use only UL or IEC approved wire for input/output connections.
- Verify that supply voltage matches voltage on luminaire label. Installation to any other connection may void the warranty.
- Wear gloves during installation to prevent injury and do not expose wiring to metal or sharp edges.
- Do not install in areas subject to combustible vapors or gases. Verify luminaire location ratings are suitable for installation environment (refer to specification sheet as needed).
- Do not restrict luminaire's ventilation by covering with material that will cause luminaire to overheat and potentially shorten the life span.



WARNING: To reduce the risk of personal injury or property damage from fire, electrical shock, falling parts, abrasions, burns and all other hazards, read all provided warnings and follow installation instructions.

This product should be installed, inspected and maintained by a qualified and licensed electrician. Installation of luminaire must be in accordance with NEC and local code requirements.

SAVE THESE INSTRUCTIONS



TOOLS REQUIRED

- Tape Measure
- Level
- Pencil
- Drill
- Phillips (cross-head) screw driver
- Hammer

PARTS REFERENCED IN THIS GUIDE

- Wall mounting cleat
- Wall anchors
- Mounting screws

NOTE:

The factory source material did not include a numbered parts diagram or quantities for the mounting hardware. Confirm exact part counts against the packing list or spec sheet before installation.

INSTALLATION INSTRUCTIONS

STEP 1 — TURN OFF POWER

Turn off the main power supply at the circuit breaker before beginning installation.

STEP 2 — MARK MOUNTING LOCATIONS

- Position the metal mounting cleat on the wall at the desired height.
- Use a level to confirm the cleat is level.
- Mark the screw hole locations.

STEP 3 — DRILL AND INSTALL MOUNTING HARDWARE

- Drill holes at the marked points.
- Insert the provided wall anchors into the drilled holes.
- Secure the mounting cleat to the wall using the supplied screws.

STEP 4 — MAKE WIRING CONNECTIONS

- Verify power is off at the breaker before touching any wiring.
- Connect the ground (green) fixture wire to the ground supply wire.
- Connect the neutral (white) fixture wire to the neutral supply wire.
- Connect the hot/live (black) fixture wire to the hot supply wire.
- If installing with a 0-10V dimming control system, connect the dimming control wires per the dimmer manufacturer's instructions.

NOTE:

Wire colors above are per the factory wiring diagram: green = ground, white = neutral, black = live/hot. The 0-10V dimming leads are not color-coded in the source diagram - confirm against the dimmer manufacturer's documentation if a dimming control system is being installed.

STEP 5 - SET THE CCT SWITCH

- Locate the 3-CCT (color temperature) shift switch on the back of the mirror.
- Set the switch to the desired color temperature setting.

CAUTION:

Set the CCT switch before mounting the mirror to the wall. The switch is not accessible once the mirror is installed.

STEP 6 - MOUNT THE MIRROR

- Lift the mirror and align it with the installed wall cleat.
- Lower the mirror onto the cleat until fully seated.
- Confirm the mirror is securely engaged with the cleat and sits level against the wall.

STEP 7 - RESTORE POWER AND TEST

- Restore power at the circuit breaker.
- Verify the LED illumination functions correctly.
- If a dimming control system is installed, verify dimming operation.

MAINTENANCE

- Clean the mirror with a soft, dry cloth only.
- Do not use chemical cleaners or abrasives.

