



IMPORTANT SAFETY PRECAUTIONS

Before you begin, read these instructions completely and carefully.

- Be certain electrical power is OFF before and during installation, maintenance and removal.
- Luminaire wiring must be properly grounded in accordance with the NEC and any applicable local code requirements.
- Use only UL or IEC approved wire for input/output connections.
- Verify that supply voltage matches voltage on luminaire label. Installation to any other connection may void the warranty.
- Wear gloves during installation to prevent injury and do not expose wiring to metal or sharp edges.
- Do not install in areas subject to combustible vapors or gases. Verify luminaire location ratings are suitable for installation environment (refer to specification sheet as needed).
- Do not restrict luminaire's ventilation by covering with material that will cause luminaire to overheat and potentially shorten the life span.
- Ensure LED luminaire has the correct polarity before installation.




WARNING: To reduce the risk of personal injury or property damage from fire, electrical shock, falling parts, abrasions, burns and all other hazards, read all provided warnings and follow installation instructions.

This product should be installed, inspected and maintained by a qualified and licensed electrician. Installation of luminaire must be in accordance with NEC and local code requirements.


SAVE THESE INSTRUCTIONS

INSTALLATION INSTRUCTIONS (JUNCTION BOX MOUNTING)


A) Loosen screws and remove the front lens. Set aside.




B) Drill appropriate knockouts (B) for wiring. The fixture supports standard 3/4" and 4" Junction box.



C) Attach the backplate to the wall, using the supplied gaskets for a weather tight seal.



D) Make electrical connections. (Black for Line, White for Neutral and Green wire for Ground).




Wire Connection


Black	○	Line
White	○	Neutral
Green	○	Ground

E) Re-attach the lens to the hinges, close the lens, then tighten the screws to fasten the lens to the backplate.


Installation is complete. 


INSTALLATION INSTRUCTIONS (CONDUIT MOUNTING)


A) Loosen screws and remove the front lens. Set aside.




B) Remove 1/2" plug from where you intend to feed conduit.



C) Drill holes (C) to secure the backplate to the wall.




D) Make electrical connections. (Black for line, White for neutral and Green wire for ground).




Wire Connection

Black	○	Line
White	○	Neutral
Green	○	Ground

E) Re-attach the lens to the hinge, close the lens set, and tighten the screws to fasten the lens set to the backplate.

Installation is complete. 



SAVE THESE INSTRUCTIONS